

MD1000_R



1 kV INSULATION TESTER

- ✓ **INSULATION TEST UP TO 200 GΩ**
- ✓ **TEST VOLTAGES: 250 V - 500 V - 1000 V**
- ✓ **SHORT CIRCUIT CURRENT: 1.5 ± 0.3 mA**
- ✓ **GUARD TERMINAL**
- ✓ **AUTO-RANGE**
- ✓ **PROGRAMMABLE TIMER**
- ✓ **PASS-FAIL TEST**
- ✓ **LOW RESISTANCE AND CONTINUITY MEASUREMENT**
- ✓ **AC/DC VOLTMETER UP TO 600 V - True RMS**
- ✓ **RECHARGEABLE BATTERY**

The Megabras **MD-1000R** is a smart, microprocessor-controlled, 1 kV insulation tester for up to **200 GΩ** resistance measuring with **250 V**, **500 V** and **1000 V** test voltage. It is a portable, hand-held, battery-powered equipment. Due to its measurement principle (actual voltage and current readings) it is a "true megohmmeter" and so the accuracy of resistance measurement is not affected by any test voltage error.

Operation is very simple and user-friendly: just connect the leads, switch-on the equipment, select the test voltage and press the Test button. Then the equipment automatically selects the most suitable range and shows the measured value in the 3½ digits display.

In order to guarantee the operator safety there are no accessible metallic parts. Output terminals are placed in the furthest and most protected area of the equipment. A light indicator shows high-voltage presence and is switched-off when the capacities (both internal and external) are discharged up to reaching a safe value.

Furthermore, it offers useful additional features: 200 mA continuity range, low resistance measurement, AC/DC voltage measurement up to 600 V, selectable timer, hold memory, and selectable resistance limits for pass-fail testing, with acoustic indication.

Surface leakage paths may affect the measurement of high value insulation resistance. The use of the *GUARD* terminal permits to remove the effect of this current, substantially improving the test result.

Due to its reduced dimensions and weight, power supply autonomy and mechanical resistance, this equipment is suitable for fieldwork.

MD 1000R - TECHNICAL SPECIFICATIONS

NOMINAL TEST VOLTAGES

250 V - 500 V - 1000 V.
Negative, DC voltage.

RESISTANCE MEASUREMENT RANGE

From 10 k Ω up to 200 G Ω .

SHORT CIRCUIT CURRENT

1.5 \pm 0.3 mA.

TEST VOLTAGE ACCURACY

-0 / +15% for resistances between 10 M Ω and open circuit.

BASIC ACCURACY

R \leq 50 G Ω : \pm 5% of reading \pm 2 digits.
R > 50 G Ω : \pm 10% of reading \pm 2 digits.

LOW RESISTANCE MEASUREMENT AND CONTINUITY TESTER

Range: 0.05 Ω to 150 Ω .
Accuracy: \pm 5% of reading \pm 2 digits.
Test current: up to 200 mA.
Continuity indicator: Activates at R < 5 Ω \pm 0.5 Ω .

BUILT-IN TIMER

5 - 10 - 15 - 30 seconds.
1 - 2 - 3 - 5 - 10 - 15 minutes.

PASS / FAIL TEST

1 - 2 - 5 - 10 - 20 - 50 - 100 - 200 - 500 M Ω .
1 - 2 - 5 - 10 - 20 - 50 - 100 G Ω .

VOLTMETER

True RMS.
Range: 0 - 600 V AC/DC.
Accuracy: \pm 3% of reading \pm 2 digits.

OVERVOLTAGE PROTECTION

600 V.

ADDITIONAL FEATURES

- Automatic Polarization Index.
- Guard terminal.
- Hold function.

SAFETY CLASS

IEC 61010-1:1990, IEC 61010-1:1992 - 2.

E.M.C

In accordance with IEC 61326-1.

ELECTROSTATIC IMMUNITY

In accordance with IEC 1000-4-2.

ELECTRO MAGNETIC IRRADIATION IMMUNITY

In accordance with IEC 61000-4-3.

POWER SUPPLY

Built-in, NiMH battery.
Autonomy: 1000 tests of 5 seconds with an interval of 25 seconds according IEC 61557-2. During the measurement is used a test resistance with the value is UN x (1000 Ω / V).

BATTERY CHARGER

Built-in, with external power supply of 12 V - 2 A.

OPERATION TEMPERATURE

-5°C to 50°C.

STORAGE TEMPERATURE

-10°C to 60°C.

HUMIDITY

95% RH (without condensation).

EQUIPMENT WEIGHT

Approx. 0.5 kg.

DIMENSIONS

102 x 195 x 46 mm.

INCLUDED ACCESSORIES

- 2 Measuring test leads.
- 1 GUARD test lead.
- 1 Power supply.
- 1 Carrying bag.
- 1 Operating instructions.

Subject to technical change without notice. This catalogue is not a contractual document.



MEGABRAS INDÚSTRIA ELETRÔNICA LTDA.
Rua Gibraltar, 172 - Santo Amaro - CEP 04755-070
São Paulo - SP - Brazil
Phone +55 11 5641-8111 - Fax +55 11 5641-9755
megabras@megabras.com - www.megabras.com



109033001