



Technical Data Sheet

Zeta 30



Zeta 30 is Analog Digital Multimeter with insulation resistance measurement , which measures VAC, VDC, VAC+DC, Frequency, mA DC, mA AC+DC, Resistance, continuity, Diode, Farad, AC current measurement with clip-on sensor and insulation resistance measurement.

Special Features

- Insulation resistance measurement up to 3G ohm
- RMS value with distorted wave from
- Auto and manual ranging modes
- Data hold function
- Display with Backlit

Application


Zeta 30 is Analog Digital Multimeter with insulation resistance measurement, which measures VAC, VDC, VAC+DC, Frequency, mA DC, mA AC+DC, Resistance, continuity, Diode, Farad, AC current measurement with clip-on sensor and insulation resistance measurement.

Product Features

| | | | |
|--|--|--|--|
| Insulation resistance measurement up to 3GΩ | Insulation resistance measurement up to 3GΩ with Test voltages selection: 50 V, 100V, 250V, 500V and 1000V. | Applicable International Safety standards | 1000 V CAT II/600V CAT III as per International Safety standard IEC 61010-1- 2001 and IEC 61557. |
| Route mean square value with distorted wave form. | Measuring principal employed permits the measurement of route mean square value (TRMS) OF AC quantities and mixed quantities (AC and DC) regardless of wave form. | Signaling in the case of a blown fuse. | The display shows "FUSE" in case of blown fuse. |
| AC Current measurement with clip-on sensor | Current measurement up to 300A with clip-on sensor having ratio 1mv/10mA. | Automatic blocking socket (ABS) | The automatic terminal blocking system prevents incorrect connection of test lead and incorrect selection of measurement quantity, which provide safety to the user. |
| Min/Max Function | By pressing min/max button instrument will start recording minimum and maximum readings. | Interface and software RISH com 100. | The multimeters are fitted with a serial RS-232 C interface via which the measured values can be transmitted to a PC. These values, electrically isolated, are transmitted to the attachable interface adaptor with infrared light through the case. |
| Temperature measurement | Temperatures from -200 to 800°C using pt100 and pt 1000 sensors. | Analog Scale | Analog scale that updates at the rate 20 times /sec to observe fluctuations in input. |
| Auto Power Off | In order to save the power of the Batteries, the meter will automatically shut OFF if it detects no activity for 10 minutes. | Continuous On Mode | In this mode, AUTO POWER OFF is disabled. |
| Continuity test | This permits resting for short circuit and open circuit. In addition to the display, a facility of sound signal is available. | DATA Hold Function | By pressing DATA HOLD button, reading on the display can be latched for Hands free operation. |
| AUTO and MANUAL ranging modes | In AUTO ranging mode the instrument automatically selects the range with best resolution depending on the applied input. In MANUAL ranging mode range is user selectable using MAN key. | NULL ZERO Correction for Resistance | For Low ohm measurement, the lead resistance can be compensated by pressing the shift key (Yellow Key) |
| Indication of negative values on the analog scale | When measuring DC quantities, also negative values are shown on the analog scale so that variations of the measured value can be observed at the Zero point. | NULL ZERO Correction for Capacitance | Null zero connection for capacitance. For nF range, stray capacitance can be compensated by shift key (Yellow Key) |
| Protection from dust and water | Instrument: IP50 For terminals : IP20 as per IEC60529 | Diode Measurement | For testing diode and transistors, diode measurement function is available. |
| | | Display with Backlit. | For clear visibility in dark conditions, Zeta 30 is featured with backlit. |

Technical Specifications

| Measuring function | Measuring range | Resolution | Input impedance | Intrinsic error of digital display ± (...% of rdg + ...digit) at reference condition | Over load capacity ¹⁾ | |
|--------------------|------------------------|-------------|-----------------|--|--|-------------------|
| | | | | | Over load value | Overload duration |
| V dc | 30.00 mV | 10 µV | >10 GΩ // <40pF | 0.5 + 3 ²⁾ | 1000 V DC AC eff / rms Sine wave | Continuously |
| | 300.0 mV | 100 µV | >10 GΩ // <40pF | 0.5 + 3 | | |
| | 3.000 V | 1 mV | 11 MΩ // <40pF | 0.25 + 1 | | |
| | 30.00 V | 10 mV | 10 MΩ // <40pF | 0.25 + 1 | | |
| | 300.0 V | 100 mV | 10 MΩ // <40pF | 0.25 + 1 | | |
| | 1000 V | 1 V | 10 MΩ // <40pF | 0.35 + 1 | | |
| V ~ | 3.000 V | 1 mV | 11 MΩ // <40pF | 1.0 + 3 (>10 Digits) | | |
| | 30.00 V | 10 mV | 10 MΩ // <40pF | | | |
| | 300.0 V | 100 mV | 10 MΩ // <40pF | | | |
| | 1000 V | 1V | 10 MΩ // <40pF | | | |
| V AC+DC | 3.000 V | 1 mV | 11 MΩ // <40pF | 1.0 + 3 (>10 Digits) | | |
| | 30.00 V | 10 mV | 10 MΩ // <40pF | | | |
| | 300.0 V | 100 mV | 10 MΩ // <40pF | | | |
| | 1000 V | 1V | 10 MΩ // <40pF | | | |
| A AC with clamp 6) | 30/300 A | 10/100mA | - | 0.5 + 5 | - | -- |
| A DC | Voltage Drop | | | | 0.36 A | Continuously |
| | 300.0 µA | 100 nA | 15 mV | 0.5+5 (>10 Digit) | | |
| | 3.000 mA | 1 µA | 150 mV | 0.5+2 | | |
| | 30.00 mA | 10 µA | 650 mV | 0.5+5 (>10 Digit) | | |
| | 300.0 mA | 100 µA | 1V | 0.5+5 | | |
| A AC+DC | 3.000 mA | 1 µA | 150 mV | 1.5+4 (>10 Digit) | 0.36 A | Continuously |
| | 300.0 mA | 100 µA | 1 V | 1.5+4 (>10 Digit) | | |
| Ω | No load voltage | | | | 1000 V DC AC eff / rms Sine wave | 10 sec |
| | 30.00 Ω | 10 mΩ | Max. 3.2 V | 0.5 + 3 ²⁾ | | |
| | 300.0 Ω | 100 mΩ | Max. 3.2 V | 0.5 + 3 | | |
| | 3.000 KΩ | 1Ω | Max. 1.25 V | 0.4 + 1 | | |
| | 30.00 KΩ | 10 Ω | Max. 1.25 V | 0.4 + 1 | | |
| | 300.0 KΩ | 100 Ω | Max. 1.25 V | 0.4 + 1 | | |
| | 3.000 MΩ | 1 KΩ | Max. 1.25 V | 0.6 + 1 | | |
| 30.00 MΩ | 10 KΩ | Max. 1.25 V | 2.0 + 1 | | | |
| → | 2.000 V | 1 mV | Max. 3.2 V | 0.25 + 1 | | |

| Measuring function | Measuring range | Resolution | Discharge resistance | U0 max. | Intrinsic error of digital display ± (...% of rdg + ...digit) at reference condition | Over load capacity ¹⁾ | |
|--|-----------------|------------|----------------------|------------------|--|---|-------------------|
| | | | | | | Over load value | Overload duration |
| Farad  | 30.00 nF | 10 pF | 250 KΩ | 2.5 V | 1.0 + 3 ²⁾ | 1000 V DC AC eff / rms Sine | 10 sec |
| | 300.0 nF | 100 pF | 250 KΩ | 2.5 V | 1.0 + 3 | | |
| | 3.000 µF | 1 nF | 25 KΩ | 2.5 V | 1.0 + 3 | | |
| | 30.00 µF | 10 nF | 25 KΩ | 2.5 V | 3.0 + 3 | | |
| Hz | | | f min V dc | f min V ~ | 0.5 + 1 ³⁾ | ≤ 3 kHz 1000 v ≤ 30 kHz; 300 V ≤100 kHz 30 V | Continuously |
| | 300.0 Hz | 0.1 Hz | 1 Hz | 45 Hz | | | |
| | 3.000 KHz | 1 Hz | 1 Hz | 45 Hz | | | |
| | 30.00 KHz | 10 Hz | 10 Hz | 45 Hz | | | |
| | 100.0 KHz | 100 Hz | 100 Hz | 100 Hz | | | |
| % | 2.0....98.0% | 0.1 % | 2 Hz | -- | 2 Hz... 1kHz ± 5 Digit ⁴⁾ 1 kHz ... 10 kHz; ± 5 Digit / kHz ⁴⁾ | | |

Technical Specifications

| Measuring function | Measuring range | | Resolution | Discharge resistance | U0 max. | Intrinsic error of digital display \pm (...% of rdg + ...digit) at reference condition | Over load capacity ¹⁾ | |
|--------------------|-----------------|------------------------|------------|----------------------|---------|---|---|-------------------|
| | | | | | | | Over load value | Overload duration |
| °C | Pt 100 | -200.0... +200.0 °C | 0.1 °C | - | -- | 2 Kelvin + 5 Digit ⁵⁾ | 1000 V DC AC eff / rms Sine | 10 sec |
| | | +200.0... +850.0 °C | 0.1 °C | | | 1.0 + 5 ⁵⁾ | | |
| | Pt 1000 | -100.0... +200.0 °C | 0.1 °C | - | -- | 2 Kelvin + 2 Digit ⁵⁾ | | |
| | | +200.0... +850.0 °C | 0.1 °C | | | 1.0 + 2 ⁵⁾ | | |

Reference conditions for Accuracy

| | |
|-------------------------------|-----------------|
| Reference temperature | 23°C ± 2K |
| Relative Humidity | 45%...55% RH |
| Waveform of measured quantity | Sinusoidal |
| Input frequency | 50 or 60 Hz ±2% |
| Battery Voltage | 8 V ± 0.1 V |

Environmental

| | |
|-----------------------|----------------------|
| Operating temperature | -20 to +50°C |
| Storage temperature | -25 to +70°C |
| Relative humidity | <75% non condensing. |
| Terminal Protection | IP20 for terminals |
| Altitude | Up to 2000 m |

Interface

| | |
|-------------------|---|
| Type | RS232C, serial, as per DIN 19241. |
| Data transmission | Optically with infrared light through the case. |
| Baud rate | 8192 bits/s. |

Battery

| | |
|-----------------|--|
| Battery Voltage | 6 x 1.5 V Cells |
| Battery type | Alkaline manganese Dioxide cell as per IEC LR 03 , ANSI 24A (Size AAA) |
| Battery Life | Minimum 600 hours on Vdc, Adc, 240 hours on Vac, Aac, For MΩISO @1000 V, 800 Measurements possible with nominal current MΩISO @500,250V, 100V, 50 V, 2400 Measurements possible with nominal current. |

Response time (After manual range selection)

| Measured Quantity/ Measured Response time | Response Time | | Transient response for step function of the measured quantity |
|--|----------------------|-----------------------|--|
| | Of Analog indication | Of digital indication | |
| VDC, VAC, A AC+DC, A AC | 0.7 s | 1.5 s | From 0 to 80 % of upper range limit. |
| 30Ω...3 MΩ | 1.5 s | 2 s | From ∞ to 50 % of upper range limit. |
| 30 MΩ | 4 s | 5 s | |
| | 0.7s | 1.5s | |
| nF, μF, °C, | | Max. 1... 3 s | From 0 to 80 % of upper range limit. |
| 300 Hz, 3KHz | | Max 2 s | |
| 30 KHz, 300 KHz | | Max 0.7 s | |
| % (1 Hz) | | Max 9 s | |
| % (≥10 Hz) | | Max 2.5 s | |


Influence Quantities and Variations

| Influence Quantity | Measuring Range | Resolution | Intrinsic error of digital display ± (...% of rdg + ...digit) at reference condition |
|--------------------|------------------|------------|--|
| V1MΩ ⁷⁾ | 0...1000 V AC+DC | 1V | 1+10 D |
| MΩIT@1000V 8) | 0...1000 V AC+DC | 1V | 1+10 D |
| MΩIT Un=50 V | 0.100...1.600 MΩ | 1KΩ | -- |
| | 01.40...16.00 MΩ | 10 KΩ | 5 + 15 D |
| MΩIT Un=100 V | 014.0...155.0 MΩ | 100 KΩ | -- |
| | 0.100...3.100 MΩ | 1KΩ | -- |
| | 02.80...31.00 MΩ | 10 KΩ | 5 + 15 D |
| MΩIT Un=250 V | 028.0...310.0 MΩ | 100 KΩ | -- |
| | 0.100...0.800 MΩ | 1KΩ | -- |
| | 00.70...08.00 MΩ | 10 KΩ | 3 + 10 D |
| | 007.0...080.0 MΩ | 100 KΩ | -- |
| MΩIT Un=500 V | 0070...0775 MΩ | 1MΩ | -- |
| | 0.100...1.600 MΩ | 1KΩ | -- |
| | 01.40...16.00 MΩ | 10 KΩ | 3 + 10 D |
| | 014.0...160.0 MΩ | 100 KΩ | -- |
| MΩIT Un=1000 V | 0140...1600 MΩ | 1MΩ | -- |
| | 0.100...3.100 MΩ | 1KΩ | -- |
| | 02.80...31.00 MΩ | 10 KΩ | 3 + 10 D |
| | 028.0...310.0 MΩ | 100 KΩ | -- |
| | 0280...3100 MΩ | 1MΩ | - |

- 1) At 0° + 40 °C
- 2) With zero adjustment, without zero adjustment + 50 digits
- 3) Range
 - 3 V ac/dc: U_e = 1.5 V eff/rms ... 100 V eff/rms
 - 30 V ac/dc: U_e = 15 V eff/rms ... 300 V eff/rms
 - 300 V ac/dc: U_e = 150 V eff/rms ... 1000 V eff/rms
- 4) On the range 3 V dc, square - wave signal positive on one side 5 ... 15 V,
f = const., not 163.84 Hz or integral multiple.
- 5) Without sensor.
- 6) Measurement with clip-on current sensor with ratio 1mv/10mA.
- 7) Discharge the DUT through 1MΩ resistance, before insulation resistance measurement. LCD displays value of voltage present on DUT.
- 8) In this switch position live circuit detection (V AD+DC) is done before insulation measurement. If voltage present is greater than 50V (AC+DC), insulation resistance measurement function is disabled and LCD displays value of voltage present on DUT.

| Influence Quantity | Range of Influence | Measured Quantity / measuring Range | Variation ¹⁾ ± (...% of rdg. +digits) |
|--------------------|--|--|--|
| Temperature | 0 °C +21 °C and +25 °C...+40°C MΩIT 0.25 + 2 | 30/300 mV dc | 1.0 + 3 |
| | | 3...300 V dc | 0.15 + 1 |
| | | 1000 V dc | 0.2 + 1 |
| | | V ~ | 0.4 + 1 |
| | | 300µA ... 300mA DC | 0.5+1 |
| | | A AC+DC | 0.75+3 |
| | | 30 Ω 2) | 0.15 + 2 |
| | | | 300 Ω 0.25 + 2 |
| | | 3 KΩ - 3 MΩ | 0.15 + 1 |
| | | 30 MΩ | 1.0 + 1 |
| | | 30 nF ²⁾ - 3 µF | 0.5 + 2 |
| | | 30 µF | 2.0 + 2 |
| | | Hz | 0.5 + 1 |
| | | % | ± 5 digits |
| -200...+200 °C | 0.5 K + 2 | | |
| +200...+850°C | 0.5 + 2 | | |

Influence Quantities and Variations


| Influence Quantity | Range of Influence | Measured Quantity / measuring Range | Variation ¹⁾ ± (...% of rdg. + ...digits) | |
|------------------------------------|--|---|---|--------------|
| Frequency of the measured quantity | 15 Hz...< 30 Hz | 3...1000 V ~ | 1.0 + 3 | |
| | 30 Hz...< 45 Hz | | 0.5 + 3 | |
| | > 65 Hz... 400 Hz | | 2.0 + 3 | |
| | Wave form of the measured quantity ³⁾ | >400 Hz...1 KHz | 3...300 V ~ | 3.0 + 3 |
| | | 20Hz ...< 45 Hz | 1000 V ~ | 3.0 + 7 |
| | | >66 Hz... 1 kHz | A~ | 2.0 + 3 |
| Crest factor CF | | 1...3 | V ~ 4) , A~ 4) | ± 1 % of rdg |
| | | 3...5 | | ± 3 % of rdg |
| Battery Voltage | |  ⁵⁾ ...< 7.9 V > 8.1 V ...10.0 V | V DC | 2 Digit |
| | V~, ADC | | 4 Digit | |
| | A AC+DC | | 6 Digit | |
| | 30Ω / 300 Ω/°C | | 4 Digit | |
| | 3 kΩ - 30MΩ, MΩIT | | 3 Digit | |
| | nF, μF, | | 1 Digit | |
| | Hz | | 1 Digit | |
| % | 1 Digit | | | |
| Relative humidity | 75% | V~,V DC A AC+DC,A DC | 3 Days | |
| | 3 Days | Ω | 1 x intrinsic error | |
| | Meter off | Hz °C | | |
| DATA | - | % | ± 1 digits | |
| MIN/MAX | - | V ac/dc , A ac/dc, clamp | ± 2 digits | |

1) With temperature: Error data apply per 10 K change in temperature.
With frequency: Error data apply to a display from 300 digits onwards.

2) With zero adjustment.

3) With unknown waveform (crest factor CF > 2), measure with manual range selection

4) With the exception of sinusoidal waveform.

5) After the "" symbol is displayed.

| Influence Quantity | Range of Influence | measuring Range | Attenuation |
|----------------------------------|--|-----------------------------|---------------------|
| Common Mode interference voltage | Noise quantity max. 1000 V | 3V~, V dc 30V~ 300 V~ | > 120 dB > 70 dB |
| | | 1000 V~ | > 60 dB |
| Normal Mode Interference Voltage | Noise quantity max. 1000 V ~ | V dc | 50dB |
| | Value of the measuring range at a time Max. 1000V~ ,50Hz, 60Hz sinusoidal | | |
| | Noise quantity max. 1000 V- | V~ | >110dB |

Influence Quantities and Variations

Applicable Standards

| | |
|-----------------------------------|---|
| For Use as a Insulation Measuring | IEC 61557: Devices for testing, measuring and monitoring protective safety measures |
| Instrument. | in system with voltages of up to 1000 V A.C. and 1500 V D.C. IEC 61557- 1: For general requirements IEC 61557- 2: For Insulation resistance measuring instruments |
| EMC | IEC 61326: Class B |
| Immunity | IEC 61000-4-2 8 KV atmosphere discharge, 4 KV contact discharge IEC 61000-4-3 : 3 V/m IEC 61010-1-2001 |

Safety

| | |
|-----------------------|---------------------------|
| IP for water & dust | IEC60529 |
| Pollution degree | 2 |
| Installation category | III |
| High Voltage Test | 3.5 kV (IEC 61010-1-2001) |

Ordering Information

| | | |
|-----------------------|---------|--|
| ZT30 - 1N000000000000 | Zeta 30 | Zeta 30 TRMS , 3 GΩ Insulation resistance measurement |
| ZT30 - 1F000000000000 | | Zeta 30 Fine Tip TRMS , 3 GΩ Insulation resistance measurement |



sifam tinsley
PRECISION INSTRUMENTATION

Sifam Tinsley Instrumentation Inc.
3105, Creekside Village Drive,
Suite No. 801, Kennesaw,
Georgia 30144 (USA)
E-mail Id : psk@sifamtinsley.com
Web : www.sifamtinsley.com
Contact No. : +1 404 736 4903

Sifam Tinsley Instrumentation Ltd.
Central Buildings, Woodland Close,
Old Woods Trading Estate,
Torquay, Devon, England, TQ27BB
Web: www.sifamtinsley.com/uk
Contact No. : +44 (0) 1803 615139